



SMTO/3

- Frontale e Porta 8 mm
- Corpo 3 mm
- Taglio Laser

- *Front and Door 8 mm*
- *Body 3 mm*
- *Laser Cut*



Digital Electronic Combination

- Lock controlled by a high performing electronic system provided by permanent memory.
- Opening/closing with recessed handle and locking by electromagnet.
- Internal power with 9 V. alkaline batteries (not included).
- Membrane keyboard with 4 leds.
- Emergency external power outlet with contacts directly on keyboard.
- Acoustic and visual signals to confirm codes, errors and internal battery deficiency.
- Nickel-plated steel bolts Ø 18 mm. (SMTO/4 Ø 22 mm).
- Lock mechanism protected by a manganese-steel plate.
- Special ledges of the door particularly resistant.
- Strong internal welding realised by a robot-controlled system.
- Front panel seam-welded to the casing by a robot-controlled system.
- Removable shelf (excluded the SMTO/1 and SMTO/2 models).
- Base and back fixing holes (2+2), anchor fixing bolts provided.
- Oven dried thermo-hardening powder painting.

Art Code	Misure esterne mm.			Misure interne mm.			Dim. porta mm.		Numero catenacci		Peso	Litri
	Alt/H	Larg/W	Prof/D	Alt/H	Larg/W	Prof/D	Alt/H	Larg/W	Oriz/Horiz	Vert	Kg	Lt
SMTO/1	220	280	150	210	270	90	130	180	2	-	10	6
SMTO/2	220	280	200	210	270	140	130	180	2	-	11	9
SMTO/3	220	350	300	210	340	240	130	250	2	-	17	19
SMTO/4	280	400	350	270	390	290	180	300	2	1+1	24,5	31

A richiesta, tutti i modelli elettronici possono essere dotati di serratura per un'apertura meccanica di emergenza con chiave di alta sicurezza a doppia mappa.

Codice prodotto di questa serie: aggiungere la lettera "P" alla fine del codice del prodotto standard.

Esempio: SMTO/1 senza chiave di emergenza diviene SMTO/1P con chiave di emergenza, SMTO/2 diviene SMTO/2P, etc.

On demand, all the electronic models can be equipped with a emergency opening with double-bitted key lock.

Product code of this series: Add a "P" at the end of the code of the article: Ex. SMTO/1 for a safe without emergency key becomes SMTO/1P for a safe with emergency key, SMTO/2 becomes SMTO/2P, etc.

Serratura di emergenza con chiave a doppia mappa mod. 1-2-3.

Emergency lock with double bitted key for mod. 1-2-3.

Serratura di emergenza con chiave a doppia mappa mod. 4.

Emergency lock with double bitted key for mod. 4.