



SMTO/3

- Frontale e Porta 8 mm
- Corpo 3 mm
- Taglio Laser

- *Front and Door 8 mm*
- *Body 3 mm*
- *Laser Cut*



Digital Electronic Combination

- Lock controlled by a high performing electronic system provided by permanent memory.
- Opening/closing with recessed handle and locking by electromagnet.
- Internal power with 9 V. alkaline batteries (not included).
- Membrane keyboard with 4 leds.
- Emergency external power outlet with contacts directly on keyboard.
- Acoustic and visual signals to confirm codes, errors and internal battery deficiency.
- Nickel-plated steel bolts Ø 18 mm. (SMTO/4 Ø 22 mm).
- Lock mechanism protected by a manganese-steel plate.
- Special ledges of the door particularly resistant.
- Strong internal welding realised by a robot-controlled system.
- Front panel seam-welded to the casing by a robot-controlled system.
- Removable shelf (excluded the SMTO/1 and SMTO/2 models).
- Base and back fixing holes (2+2), anchor fixing bolts provided.
- Oven dried thermo-hardening powder painting.

Art	Misure esterne mm.			Misure interne mm.			Dim. porta mm.		Numero catenacci		Peso	Litri
	Code	External dim. mm.			Internal dim. mm.			Door dim. mm.		Number of bolts		
	Alt/H	Larg/W	Prof/D	Alt/H	Larg/W	Prof/D	Alt/H	Larg/W	Oriz/Horiz	Vert	Kg	Lt
SMTO/1	220	280	150	210	270	90	130	180	2	-	10	6
SMTO/2	220	280	200	210	270	140	130	180	2	-	11	9
SMTO/3	220	350	300	210	340	240	130	250	2	-	17	19
SMTO/4	280	400	350	270	390	290	180	300	2	1+1	24,5	31

A richiesta, tutti i modelli elettronici possono essere dotati di serratura per un'apertura meccanica di emergenza con chiave di alta sicurezza a doppia mappa.

Codice prodotto di questa serie: aggiungere la lettera "P" alla fine del codice del prodotto standard.

Esempio: SMTO/1 senza chiave di emergenza diviene SMTO/1P con chiave di emergenza, SMTO/2 diviene SMTO/2P, etc.

On demand, all the electronic models can be equipped with a emergency opening with double-bitted key lock.

Product code of this series: Add a "P" at the end of the code of the article: Ex. SMTO/1 for a safe without emergency key becomes SMTO/1P for a safe with emergency key, SMTO/2 becomes SMTO/2P, etc.

Serratura di emergenza con chiave a doppia mappa mod. 1-2-3.

Emergency lock with double bitted key for mod. 1-2-3.

Serratura di emergenza con chiave a doppia mappa mod. 4.

Emergency lock with double bitted key for mod. 4.